

SN74BCT657

OCTAL TRANSCEIVER WITH PARITY GENERATOR/CHECKER AND 3-STATE OUTPUTS

SCBS079B – NOVEMBER 1991 – REVISED APRIL 1994

- **State-of-the-Art BiCMOS Design**
Significantly Reduces I_{CCZ}
- **ESD Protection Exceeds 2000 V Per**
MIL-STD-883C, Method 3015; Exceeds
200 V Using Machine Model (C = 200 pF,
R = 0)
- **3-State B Outputs Sink 48 mA or 64 mA**
and Source 12 mA or 15 mA
- **Package Options Include Plastic**
Small-Outline (DW) Packages and Standard
Plastic 300-mil DIPs (NT)

description

The SN74BCT657 contains eight noninverting transceivers with 3-state outputs and an 8-bit parity generator/checker. It is intended for bus-oriented applications.

The transmit/receive (T/\bar{R}) input determines the direction of the data flow through the bidirectional transceivers. When T/\bar{R} is high, data is transmitted from the A port to the B port. When T/\bar{R} is low, data is received at the A port from the B port.

When the output-enable (\overline{OE}) input is high, both the A and B ports are placed in a high-impedance state (disabled). The ODD/ \overline{EVEN} input allows the user to select between odd or even parity systems.

When transmitting from A port to B port (T/\bar{R} high), PARITY is an output from the generator/checker. When receiving from B port to A port (T/\bar{R} low), PARITY is an input.


When transmitting (T/\bar{R} high), the parity-select (ODD/ \overline{EVEN}) input is made high or low as appropriate. The A port is then polled to determine the number of high bits. The PARITY output goes to the logic state determined by the parity-select (ODD/ \overline{EVEN}) input and the number of high bits on A port. When ODD/ \overline{EVEN} is low (for even parity) and the number of high bits on A port is odd, the PARITY will be high, transmitting even parity. If the number of high bits on A port is even, the PARITY will be low, keeping even parity.

When in the receive mode (T/\bar{R} low), the B port is polled to determine the number of high bits. If ODD/ \overline{EVEN} is low (for even parity) and the number of highs on B port is as follows:

- Odd and the PARITY input is high, then \overline{ERR} will be high signifying no error.
- Even and the PARITY input is high, then \overline{ERR} will be low indicating an error.

The SN74BCT657 is characterized for operation from 0°C to 70°C.

DW OR NT PACKAGE (TOP VIEW)



SN74BCT657

OCTAL TRANSCEIVER WITH PARITY GENERATOR/CHECKER


AND 3-STATE OUTPUTS

SCBS079B – NOVEMBER 1991 – REVISED APRIL 1994

FUNCTION TABLE

NUMBER OF A OR B INPUTS THAT ARE HIGH	INPUTS			INPUT/OUTPUT PARITY	OUTPUTS	
	\overline{OE}	T/\overline{R}	ODD/ \overline{EVEN}		\overline{ERR}	OUTPUT MODE
0, 2, 4, 6, 8	L	H	H	H	Z	Transmit
	L	H	L	L	Z	Transmit
	L	L	H	H	H	Receive
	L	L	H	L	L	Receive
	L	L	L	H	L	Receive
	L	L	L	L	H	Receive
1, 3, 5, 7	L	H	H	L	Z	Transmit
	L	H	L	H	Z	Transmit
	L	L	H	H	L	Receive
	L	L	H	L	H	Receive
	L	L	L	H	H	Receive
	L	L	L	L	L	Receive
Don't care	H	X	X	Z	Z	Z

logic symbol†




† This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.

SN74BCT657

OCTAL TRANSCEIVER WITH PARITY GENERATOR/CHECKER AND 3-STATE OUTPUTS

SCBS079B – NOVEMBER 1991 – REVISED APRIL 1994

logic diagram (positive logic)



SN74BCT657

OCTAL TRANSCEIVER WITH PARITY GENERATOR/CHECKER AND 3-STATE OUTPUTS

SCBS079B – NOVEMBER 1991 – REVISED APRIL 1994

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)[†]

Supply voltage range, V_{CC}	–0.5 V to 7 V
Input voltage range, V_I (see Note 1)	–0.5 V to 7 V
Voltage range applied to any output in the disabled or power-off state, V_O	–0.5 V to 5.5 V
Voltage range applied to any output in the high state, V_O	–0.5 V to V_{CC}
Input clamp current, I_{IK} ($V_I < 0$)	–30 mA
Current into any output in the low state, I_O	128 mA
Operating free-air temperature range	0°C to 70°C
Storage temperature range	–65°C to 150°C

[†] Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTE 1: The input and output negative-voltage ratings may be exceeded if the input and output clamp-current ratings are observed.

recommended operating conditions (see Note 2)

		MIN	NOM	MAX	UNIT
V_{CC}	Supply voltage	4.5	5	5.5	V
V_{IH}	High-level input voltage	2			V
V_{IL}	Low-level input voltage			0.8	V
I_{IK}	Input clamp current			–18	mA
I_{OH}	High-level output current			–3	mA
				–15	
I_{OL}	Low-level output current			24	mA
				64	
T_A	Operating free-air temperature	0		70	°C

NOTE 2: Unused or floating pins (input or I/O) must be held high or low.



SN74BCT657

OCTAL TRANSCEIVER WITH PARITY GENERATOR/CHECKER AND 3-STATE OUTPUTS

SCBS079B – NOVEMBER 1991 – REVISED APRIL 1994

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS		MIN	TYP†	MAX	UNIT
V_{IK}		$V_{CC} = 4.5\text{ V}$, $I_I = -18\text{ mA}$				-1.2	V
V_{OH}	Any output	$V_{CC} = 4.5\text{ V}$, $I_{OH} = -3\text{ mA}$		2.4	3.3		V
	B port, PARITY, \overline{ERR}	$V_{CC} = 4.5\text{ V}$, $I_{OH} = -15\text{ mA}$		2	3.1		
	Any output	$V_{CC} = 4.75\text{ V}$, $I_{OH} = -3\text{ mA}$		2.7			
V_{OL}	A port	$V_{CC} = 4.5\text{ V}$, $I_{OL} = 24\text{ mA}$		0.35	0.5		V
	B port, PARITY, \overline{ERR}	$V_{CC} = 4.5\text{ V}$, $I_{OL} = 64\text{ mA}$		0.42	0.55		
I_I	T/\overline{R}	$V_{CC} = 0$, $V_I = 7\text{ V}$, $\overline{OE} = 4.5\text{ V}$				20	μA
	\overline{OE}	$V_{CC} = 0$, $V_I = 7\text{ V}$, $T/\overline{R} = 4.5\text{ V}$				20	
	ODD/EVEN	$V_{CC} = 0$, $V_I = 7\text{ V}$				20	
	A port	$V_{CC} = 5.5\text{ V}$, $V_I = 2.7\text{ V}$				100	
	B port, PARITY	$V_{CC} = 5.5\text{ V}$, $V_I = 2.7\text{ V}$				200	
I_{IH}^\ddagger	A or B port, PARITY	$V_{CC} = 5.5\text{ V}$, $V_I = 2.7\text{ V}$				200	μA
	T/\overline{R} , \overline{OE}	$V_{CC} = 5.5\text{ V}$, $V_I = 2.7\text{ V}$				20	
	ODD/EVEN	$V_{CC} = 5.5\text{ V}$, $V_I = 2.7\text{ V}$				20	
I_{IL}^\ddagger	A or B port, PARITY	$V_{CC} = 5.5\text{ V}$, $V_I = 0.5\text{ V}$				-70	μA
	T/\overline{R} , \overline{OE}	$V_{CC} = 5.5\text{ V}$, $V_I = 0.5\text{ V}$				-20	
	ODD/EVEN	$V_{CC} = 5.5\text{ V}$, $V_I = 0.5\text{ V}$				-20	
I_{OS}^\S	A port	$V_{CC} = 5.5\text{ V}$, $V_O = 0$		-60		-200	mA
	B port, PARITY, \overline{ERR}	$V_{CC} = 5.5\text{ V}$, $V_O = 0$		-125		-300	
I_{OZH}	\overline{ERR}	$V_{CC} = 5.5\text{ V}$, $V_O = 2.7\text{ V}$				50	μA
I_{OZL}	\overline{ERR}	$V_{CC} = 5.5\text{ V}$, $V_O = 0.5\text{ V}$				-50	μA
I_{CCL}		$V_{CC} = 5.5\text{ V}$, Outputs open				90	mA
I_{CCH}		$V_{CC} = 5.5\text{ V}$, Outputs open				2	mA
I_{CCZ}		$V_{CC} = 5.5\text{ V}$, Outputs open				1	mA
C_i	Control input	$V_{CC} = 5\text{ V}$, $V_I = 2.5\text{ V or }0.5\text{ V}$			6.5		pF
C_{io}	A port	$V_{CC} = 5\text{ V}$, $V_O = 2.5\text{ V or }0.5\text{ V}$			10		pF
	B port, PARITY	$V_{CC} = 5\text{ V}$, $V_O = 2.5\text{ V or }0.5\text{ V}$			14		
C_o	\overline{ERR}	$V_{CC} = 5\text{ V}$, $V_O = 2.5\text{ V or }0.5\text{ V}$			10		pF

† All typical values are at $V_{CC} = 5\text{ V}$, $T_A = 25^\circ\text{C}$.

‡ For I/O ports, the parameters I_{IH} and I_{IL} include the off-state output current.

§ Not more than one output should be tested at a time, and the duration of the test should not exceed one second.

SN74BCT657

OCTAL TRANSCEIVER WITH PARITY GENERATOR/CHECKER AND 3-STATE OUTPUTS

SCBS079B – NOVEMBER 1991 – REVISED APRIL 1994

switching characteristics over recommended ranges of supply voltage and operating free-air temperature, $C_L = 50$ pF (unless otherwise noted) (see Note 3)

PARAMETER	FROM (INPUT)	TO (OUTPUT)	$V_{CC} = 5$ V, $T_A = 25^\circ\text{C}$			MIN	MAX	UNIT
			MIN	TYP	MAX			
t_{PLH}	A or B	B or A	1.1	3.1	6	1.1	6.6	ns
t_{PHL}			2	5.3	8.5	2	9	
t_{PLH}	A	PARITY	3	7.4	12.7	3	15.4	ns
t_{PHL}			4.6	8.6	14.1	4.6	15.9	
t_{PLH}	ODD/ $\overline{\text{EVEN}}$	PARITY, ERR	1.1	4.1	6.4	1.1	7.1	ns
t_{PHL}			2.6	5.5	8.3	2.6	9	
t_{PLH}	B	$\overline{\text{ERR}}$	3.1	7.4	12.6	3.1	15.3	ns
t_{PHL}			4.4	6.5	13.3	4.4	15.5	
t_{PLH}	PARITY	$\overline{\text{ERR}}$	3.4	7.7	10.7	3.4	13.2	ns
t_{PHL}			5.5	8.8	12	5.5	13.9	
t_{PZH}	$\overline{\text{OE}}$	A, B, PARITY, or $\overline{\text{ERR}}$	1.8	5.1	7.7	1.8	9.1	ns
t_{PZL}			3.2	6.7	14.2	3.2	16.3	
t_{PHZ}	$\overline{\text{OE}}$	A, B, PARITY, or $\overline{\text{ERR}}$	2.6	5.7	8	2.6	9.1	ns
t_{PLZ}			2	5	7.4	2	8	

NOTE 3: Load circuits and voltage waveforms are shown in Section 1.

IMPORTANT NOTICE

Texas Instruments (TI) reserves the right to make changes to its products or to discontinue any semiconductor product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

TI warrants performance of its semiconductor products and related software to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Certain applications using semiconductor products may involve potential risks of death, personal injury, or severe property or environmental damage ("Critical Applications").

TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS.

Inclusion of TI products in such applications is understood to be fully at the risk of the customer. Use of TI products in such applications requires the written approval of an appropriate TI officer. Questions concerning potential risk applications should be directed to TI through a local SC sales office.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein. Nor does TI warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used.